

A METHOD AND A DEVICE FOR REMINDING OF AN UNANSWERED CALL

FIELD OF THE INVENTION

- 5 The present invention relates to a method and a device for reminding of an unanswered call.

BACKGROUND OF THE TECHNOLOGY

- 10 When using a mobile phone there often occur situations where the person receiving is unable to answer an incoming call. In public switched phones, it is already enough for this kind of situation that the recipient is not in the vicinity of a telephone device. Mobile phones have provided people with an opportunity to be within reach all the time. After the problem of physical reachability was solved,
- 15 mental reachability has become a new problem. Although the recipient would always carry with him a mobile phone, there still occur situations where he is either unable or unwilling to answer an incoming call. These kinds of situations are, for example, important meetings, negotiations and leisure-time activities.
- 20 As a known solution to the problem in these kinds of situations, an automatic telephone answering set is generally used, which in the case of mobile phones can be implemented by a separate answering unit to be attached to the mobile phone or as a service provided by a mobile phone operator at a mobile services switching centre. In addition, in the case of mobile phones, in many mobile
- 25 communication systems the telephone number of a caller simultaneously remains, when the call is left unanswered, in the register of unanswered calls in the memory unit of the mobile phone, and a notice of the unanswered call will appear on the display of the mobile phone. The user may later retrieve the telephone number of the unanswered call from the register of unanswered calls, for example,
- 30 by acknowledging the notice of the unanswered call as received from the user interface of the mobile phone. However, when the user rejects an incoming call, for example, by pressing the on-hook key (call ending key), a note of the call that came in goes into the register of received calls and not into the register of unanswered calls. When the user rejects an incoming call, no reminder text will
- 35 either appear on the display of the mobile phone of a call that came in, but was left unanswered. The presented solutions are known, for example, from Nokia's mobile phone series 5100 and 6100.

In the solution presented above, the problem is, however, that after once opening the register of unanswered calls the user of the phone will no more get a reminder of his unanswered calls. One unanswered call does not cause a major problem, but as the number of unanswered calls increases, it will become difficult to
5 remember to answer all the calls. Another problem is that there are n pieces of memory locations in the "unanswered calls" register, where n typically is 10-20. Said register being full when a new unanswered call comes into the register, the number of which is not already in the register, the last number in the register will be removed. Additional problems are also caused by the storing of the telephone
10 numbers of unanswered and rejected calls in different registers although, in both cases, the call was not answered. For example, for a businessman, the consequences of forgetting to answer an unanswered call may be serious wherefore it is well founded to contribute to it that all unanswered calls will be answered.

15 SUMMARY OF THE INVENTION

Now, a method and a device have been invented for reminding a user of a mobile phone of an unanswered call.

20 According to a first aspect of the invention, there is implemented a mobile phone comprising means for receiving a call, identification means for identifying the caller number from the call that comes into the device, a clock for determining the course of time, and a memory unit for storing information, characterised in that
25 there is a functional connection between the identification means and the memory unit, the identification means are arranged to transfer the information referring to the number of the caller of an unanswered call into the memory unit on the basis of a first response when the call is not answered, and the memory unit is arranged to remind the user of the mobile phone of the unanswered call, on the basis of a
30 second response obtained from the clock, of the reaching of a specific point of time.

According to a second aspect of the invention, there is implemented a method for reminding of the answering of unanswered calls, in which method a call comes
35 into a mobile phone, the telephone number of the caller is identified from the call that comes into the mobile phone, characterised in that the method comprises leaving the call unanswered, transferring the information referring to the telephone number of the caller of the unanswered call into a memory unit on the basis of a

first response, and reminding the user of the unanswered call at a later point of time.

5 In a preferred embodiment of the invention, a clock, a calendar and a user interface that are in present mobile phones are utilised and, thus, they are part of said device for reminding of an unanswered call. With the help of the invention, it is easy to contribute to the answering of all unanswered calls and, hence, to contribute to it that no important contacts would be forgotten.

10 In the preferred embodiment of the invention, the telephone number of an unanswered call and/or other identification information referring to the call are automatically transferred into the electronic calendar of the device when there is a desire to be reminded of the unanswered call at a later point of time (in this connection, by reminding it is meant that there is a note of the matter to be
15 reminded of in the memory unit of the mobile phone). The user does not have to separately write a reminder, which makes the use of the method and the device easier. Furthermore, in connection with getting a reminder, the user may on the basis of the identification information in the calendar relating to the unanswered call initiate a call to the number in question without separately having to start the
20 call initiation procedures by looking up the telephone number in question in the phone directory or in the register of unanswered calls of the phone. Initiating a call directly from the calendar facilitates and speeds up the answering of unanswered calls.

25 The user may either himself separately determine, for example, in connection with leaving a call unanswered, whether or not the information on the unanswered call is transferred into the calendar for reminding to be effected at a later point of time, or the method and the device can be set to automatically transfer the information on unanswered calls into the calendar, or the method and the device can be set to
30 only transfer the information on the telephone numbers of specific unanswered calls into the calendar for reminding. The calendar can be set to preferably remind the user in the form of a sound signal and a reminder text of an unanswered call that comes onto the display at a pre-determined point of time of reminding, which point of time of reminding the user may set himself, for example, when leaving a
35 call unanswered, or the device can automatically set said point of time of reminding, for example, on the basis of settings made in advance.

According to the invention, the device can be set to also give said reminder of an unanswered call, for example, when the user changes the mode of operation of his mobile phone by changing the mode of the phone, for example, from silent to normal, or when the user separately requests a reminder of unanswered calls by a pre-determined command. The reminder can preferably be set to be given again at another later point of time if the user at the previous time of reminding did not call the unanswered call or he did not acknowledge the reminding function to be terminated as regards the unanswered call in question in connection with the previous reminder.

By the invention, a simple way is established to help remember to answer any unanswered calls. In the implementation of the invention, it is possible to utilise the clock, calendar and user interface that already exist in present mobile phones. The calendar can preferably give the user a reminder in the form of a sound signal. The reminding function can be initiated, for example, when the time passed has reached a pre-determined threshold value or when the user changes the mode of operation of his mobile phone, for example, from a silent mode into a normal mode.

Moreover, as the user can carry with him the mobile phone all the time he will be able to have reminders just about any time of day he wishes, i.e. during office hours as well as out of office hours, and during weekends and vacations.

BRIEF DESCRIPTION OF THE DRAWINGS

In the following, the invention will be described in detail by referring to the enclosed drawings, in which

Figure 1 shows as a block diagram a device according to the invention for reminding of an unanswered call;

Figure 2 shows a data burst generally used in the transmission of information in wireless digital networks;

Figure 3 shows one implementation of a user interface when receiving a call;

Figure 4 shows a flow diagram of the functional progress of leaving a call unanswered;

Figure 5a shows a preferred implementation of the invention that utilises a calendar; and

Figure 5b shows an implementation for a reminder coming from a calendar through a display to a user on the basis of a pre-determined response.

DETAILED DESCRIPTION

5

Figure 1 shows a device according to an embodiment of the invention, which comprises a transceiver part 10 and a device controlling part 15. The transceiver part includes an antenna 11, a Duplex filter 12, a receiving branch 13, and a transmitting branch 14. The transceiver part is connected with a unit (MCU, Master Controlling Unit) 16 located in the device controlling part 15 that controls the other parts, which is, e.g. a microprocessor. The unit 16 that controls the device is arranged to identify, on the basis of a program stored in a memory unit 20, the number of the caller from a CLI (Caller Line Identification) part 18 of the incoming data burst. Lower down, the figure shows the physical block diagram of the device controlling part 15 and farther up, the figure shows the functional block diagram of the device controlling part 15. The unit that controls the device further comprises a clock 17, e.g. the clock of a microprocessor, for determining the course of time and functions implemented by programs stored in the memory unit 20 for creating a call 22 and for recording a reminder in the memory unit 20. Said call creation function 22 is functionally connected with said memory unit so that it is possible to transfer from the memory unit a telephone number to the call creation function. The caller line identification application 18 is connected with the memory unit 20, wherein the information relating to an unanswered call can be stored. The caller line identification application 18 is also connected with a user interface 19 through which the user can control the function for reminding of the information stored in the memory unit.

Present wireless communication, for example, TDMA (Time-Division Multiple-Access) is based on transferring data bursts of short duration between a base transceiver station and a mobile phone. The use of such short bursts in the transmission of information enables several users to simultaneously communicate on the same frequency band. In wireless communication, where a frequency band is limited, this type of simultaneous multiple use of a band, based on data bursts, has proved useful.

35

Figure 2 shows in general said data burst 25 of this type. The data burst consists of a caller line, i.e. a so-called A-subscriber identification 26 (also known as CLI), which comprises the information on the telephone number of the caller and with

the help of which information the mobile phone can open a connection with the phone of the caller of the incoming call. A data burst receiver, i.e. a so-called B-subscriber identification 27, which comprises the information on the telephone number of the recipient, with the help of which information the mobile phone of the recipient is able to identify the data bursts coming thereto. In addition, the data burst comprises transferable information 28. From the caller line identification 26, the telephone number of the caller can be found out by the caller line identification function of the unit that controls the device, on the basis of which the caller can be identified.

Figure 3 shows a preferred implementation for the user interface 19 of a device according to the invention, which comprises a selector 32 for answering an incoming call, a selector 33 for leaving an incoming call unanswered and for transferring for being reminded of at a later point of time, a selector 34 for leaving an incoming call unanswered without later being reminded of the unanswered call. Furthermore, the user interface comprises selectors 35 for changing the mode of operation of a mobile phone, for selecting the point of time of reminding and for pre-controlling the reminding function, and a display screen 36 for bringing a desired type of reminder text to be displayed to the user in connection with reminding of the unanswered call. Said selectors are, for example, keys that can be so-called SOFT keys, i.e. the function connected with the key is shown as a command on the display and further, said key may have several different functions depending on the mode of the device. Thus, for the above-mentioned selectors 32-34, the above-mentioned functions will be activated when a call comes into the device.

Figure 4 shows a flow diagram that illustrates one preferred implementation of a method according to the invention, in which method a call comes into a mobile phone (step 41), whereupon it receives a message of this, such as, e.g. the data burst 25 mentioned above. The telephone number of the caller is identified from the data burst by the caller line identification function in the unit controlling the device (step 42). When the call comes in, it is checked whether the user answers the incoming call or not (step 43). In the situation where the user answers the incoming call, by pressing the selector 32 a voice (call) connection is opened between the caller and the recipient (step 44). If the user rejects the incoming call by pressing the selector 34, whereupon he neither wants himself to be reminded of the unanswered call, the call set-up attempt is cut off and the information relating to the telephone number of the caller are transferred into the register of

unanswered calls, wherein the telephone number of the caller in question can be found at a later stage (step 45).

5 In a situation where the user is unable to answer a call but, however, wants to be reminded of the unanswered call, by pressing the selector 33 the information relating to the telephone number of the caller is transferred into the register of unanswered calls and, at the same time, said number information is also transferred into the calendar (step 46) for reminding. Alternatively, if the user does not react in any way to an incoming call, the method and the device can preferably
10 be pre-set to transfer in this kind of situation the information relating to the unanswered call, in addition to the register of unanswered calls, automatically into the calendar. This being the case, a notification will remain on the display of the mobile phone of the unanswered call, which information refers to new telephone numbers entered in the "unanswered calls" register, and the user will also get a
15 reminder of the call left unanswered.

In a situation, where the user has been unable to answer a call but, however, has wanted to be reminded of the unanswered call, it is checked whether the user wants to set himself some point of time of reminding or whether the reminding
20 delay pre-determined in the device will be used (step 47). If the user wants to set the point of time of reminding in connection with the selecting of the reminding function or later, the reaching of this point of time is set for being monitored (step 48). Alternatively, if the user does not determine the time of reminding or if the user has not originally reacted in any way to the incoming call, the pre-determined
25 reminding delay is set as the time, the reaching of which will be monitored with the help of the clock of the device (step 49).

After setting the reminding delay, it will be waited that the time limit is reached or the user carries out through the user interface some pre-determined function that
30 launches the reminder. Said pre-determined function could be, for example, the changing of the mode of operation of the mobile station, e.g. from a conference (call) mode (no sound, a notification of an incoming call by flashing the lights of the display) into a normal mode (notifying of an incoming call primarily with the help of the phone's ringing tone), whereupon the mobile phone knows that the
35 meeting has ended and the user now has an opportunity to answer the calls that have come in, so the user can be shown a list of the calls that have come in. Said second pre-determined function could be the giving of some command to the mobile phone from the user interface by pressing some selector, whereupon the

mobile phone knows that the user has, for example, returned from a run and is now more prepared to answer the calls that have come in, so the user can be given a reminder of the calls that have come in, or the giving of a pre-determined reminding command to the mobile phone, whereupon the mobile phone knows that exactly at that moment the user wants to be reminded of the unanswered calls. Switching on the current in the mobile phone could also be one possible pre-determined function, whereupon the mobile phone knows that the user is, for example, awake (if he is accustomed to keeping his mobile phone switched off at nights) and, thus, ready to answer the calls that have come in, so the user can be given a reminder of the unanswered calls (step 50).

When one of the above mentioned situations occurs, the user is preferably given a reminder of an unanswered call, for example, using one of the following methods or some combination of these methods: through a sound signal, if the mobile phone is not in a silent mode; with a reminder text that appears on the display screen; through light signals that appear on the display screen of the mobile phone; through tactile alerts of the mobile phone (step 51).

In connection with giving a reminder and thereafter, it is monitored whether the user reacts in any way to the reminder, for example, by switching off the reminding function in the middle or by calling the number that is the object of the reminder (step 52). If the user does not react in any way to the reminder, the device will set a new pre-determined reminding delay (step 53), after which the user will be reminded again of the unanswered call (step 51). Alternatively, if the user reacts to the given reminder, it is checked whether the user wants yet a new reminder of the unanswered call in question or whether he wants to stop the reminding function as for the unanswered call in question (step 54). In the event that the user wants a new reminder, a new reminding time will be set (step 53) either by the user or automatically, in which case the user will again be reminded of the unanswered call (step 51), after which it is re-checked whether the user wants yet a new reminder, etc. If the user wants no more reminders of the unanswered call in question, the information relating to the unanswered call in question will be removed from the memory unit and the reminding function will be terminated as regards this unanswered call dealt with (step 55).

35

As the user can carry with him the mobile phone all the time he will be able to have reminders just about any time of day he wishes, i.e. during office hours as well as out of office hours, and during weekends and vacations.

In a special situation, where the identifying of the telephone number of the caller of an incoming call does not succeed or where the CLI field (26) of the incoming data burst is empty, for example, calls coming from abroad, the user can

5 preferably either be reminded of an unanswered or rejected call or, if the user so desires, not to be reminded of an unanswered call in this kind of situation. The user may preferably set the device always to remind of unanswered or rejected calls, wherein the CLI field is empty, or the user may set the device to remind of such a call when separately requested, or the user may set the device not to
10 remind of an unanswered call in these kinds of situations.

Figure 5a shows a preferred implementation that utilises an electronic calendar for reminding of an unanswered call. A user interface 19 of a mobile phone comprises a display 36. In Figure 5a, there is shown on the display by way of example a
15 calendar application that the invention utilises. The calendar application may preferably comprise several different functional application parts on the display. For example, a first part 60 preferably informs here the functionality of SOFT keys 32-34 in the mobile phone's mode of operation in question. A second part 61 preferably shows on the display, for reminding the user, the day view of the
20 calendar, on a day selected by the user, of the information with the times of reminding, referring to the calls left unanswered that he has received. A third part 62 preferably comprises the month view of the calendar.

Figure 5b shows a preferred implementation of a reminder to be given to a user
25 through a display, on the basis of a pre-determined response. In the figure, said response is the reaching of the point of time of reminding. A user interface 19 of a mobile phone comprises a display 36. In Figure 5b, the display 36 is divided into three different functional parts. In this case, a first part 63 gives a summary of the information referring to the unanswered calls to be reminded of, in the form of a
30 list. Said list preferably comprises, for example, the identification information of an unanswered call (e.g. the name or telephone number of the caller) and other information, such as, e.g. the time of reminding and the time the call was received. A second part 64 preferably informs the user of the more detailed identification information referring to the call, and a third part of the display 65 informs the
35 functionality of SOFT keys 32-34 in the mobile phone's mode of operation in question.

This paper presents the implementation and embodiments of the present invention, with the help of examples. A person skilled in the art will appreciate that the present invention is not restricted to details of the embodiments presented above, and that the invention can also be implemented in another form without deviating from the characteristics of the invention. The embodiments presented
5 above should be considered illustrative, but not restricting. Thus, the possibilities of implementing and using the invention are only restricted by the enclosed claims. Consequently, the various options of implementing the invention as determined by the claims, including the equivalent implementations, also belong to
10 the scope of the invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
22